

# CAN-CR120/HV

CAN / CAN FD repeater with screw terminals and 3 kV galvanic isolation



The CAN-CR120/HV is used for galvanic isolation of two segments of a CAN / CAN FD network. As a special feature, the repeater separates a defective segment from the rest of the network, allowing the remaining network to continue working. After the fault has been eliminated, the segment is automatically switched back to the network. The galvanic isolation is provided for the CAN / CAN FD segments as well as for the power supply.

## Features and Benefits

- Line protection up to 3 kV
- CAN and CAN FD interfaces in one device
- Cost savings due to simple wiring
- Increased system reliability
- Almost no influence on real-time behavior

## Technical specifications

<b>Display</b>	Transmit and defective segment (two duo LEDs, one for each segment), Power (one LED)
<b>CAN bus interface</b>	ISO 11898-2 with CAN choke. Two screw terminals. Available with and without integrated CAN termination.
<b>CAN baudrate</b>	Up to 1 Mbit/s
<b>CAN FD bus interface</b>	ISO CAN FD and nonISO CAN FD
<b>CAN FD baudrate</b>	500 kbit/s (arbitration bitrate) and up to 4 Mbit/s (flexible data rate)
<b>Delay</b>	typ. 175 ns (corresponds to ~35 m bus length)
<b>Power supply</b>	9-36 V DC, typ. 70 mA, max. 100 mA, through terminals
<b>Galvanic isolation</b>	3 kV DC / 1 sec, 1500 V AC / 1 min; CAN 1, CAN 2 and power supply are galvanically isolated from each other.
<b>Certification</b>	CE, FCC
<b>Temperature range</b>	-20 °C ... +70 °C
<b>Housing, size</b>	Plastic enclosure, 22.5 x 105 x 114 mm